

FUELING YOUR POWER ADDICTION

Burger Tuning JB4 Port Injection Controller Wiring Configurations

				<u> </u>	
Platform		Wire	Color	Connects to	Additional notes
E-Series	N54	Power	Red	12V switched	Green connector in DME box, connect to either orange wire
		Ground	Black	Chassis	Shock tower
		RPM	Purple	Pin 21 on JB4 gray connector	As counted from the female connectror
		TMAP	Yellow	Pin 9 on JB4 DB9 connector	JB4 USB cable or JB4 Mobile Connect Kit required
		Signal	White	Pin 15 on JB4 DB25 connector	Set Meth Scaling to 100. If occupied, remove meth kit.
		E. Sensor	White	Pin 2 on JB4 DB25 connector	Set FUA to 58, ethanol content reported as DutyC
	-				
		Wire	Color	Connects to	Additional notes
		Power	Red	12V switched	Large red wire in black connector at back of DME box
		Ground	Black	Chassis	Shock tower
	N55	RPM	Purple	Dark gray/black wire in DME box	Find the small textured wire that extends through DME box
	New PWM chip	TMAP	Yellow	Pin 1 on JB4 DB25 connector	
	needed	Signal	White	Pin 16 on JB4 DB25 connector	Set Meth Scaling to 100. If occupied, remove meth kit.
		E. Sensor	White	Pin 3 on JB4 DB25 connector	Set FUA to 58, E content report as DutyC
Platform		Wire	Color	Connects to	Additional notes
		Power	Red	12V	Attaches to jump terminal with fuse assembly
F-Series	N55	Ground	Black	Chassis	Shock tower
	PWG	RPM	Purple	Pin 3 of JB4 OBDII 4 pin connector	Insert pin from purple extention wire in to slot below green wire
	New PWM	TMAP	Yellow	Pin 1 on JB4 DB25 connector	
	chip	Signal	White	Pin 16 on JB4 DB25 connector	Set Meth Scaling to 100. If occupied, remove meth kit.
	needed	E. Sensor	White	Pin 3 on JB4 DB25 connector	Set FUA to 58, E content report as DutyC
		Wire	Color	Connects to	Additional notes
		Power	Red	12V	Attaches to jump terminal with fuse assembly
		Ground	Black	Chassis	Shock tower
	N55	RPM	Purple	Pin 3 of JB4 OBDII 4 pin connector	Insert pin from purple extention wire in to slot below green wire
	EWG	TMAP	Yellow	Pin 1 on JB4 DB25 connector	
	EWG	Signal	White	Pin 14 on JB4 DB25 connector	Set Meth Scaling to 100. If occupied, remove meth kit.
		E. Sensor	White	Pin 3 on JB4 DB25 connector	Enable bit 3, E content report as DutyC
		753			
		Wire	Color	Connects to	Additional notes
		Power	Red	12V	Attaches to jump terminal with fuse assembly
		Ground	Black	Chassis	Shock tower
	(1)	RPM	Purple	Pin 3 of JB4 OBDII 4 pin connector	Insert pin from purple extention wire in to slot below green wire
	S55	TMAP	Yellow	Pin 1 on JB4 DB25 connector	

Set Meth Scaling to 100. If occupied, remove meth kit.

Enable bit 3, E content report as DutyC

Signal

E. Sensor

White

White

Pin 16 on JB4 DB25 connector

Pin 3 on JB4 DB25 connector